



Eyb Megaswitch® 3.0 Type E

2 humbuckers # 2

position	sound	hum cancelling
1	bridge humbucker	x
2	bridge humbucker split, bridge side coil	
3	bridge humbucker + neck humbucker, both split, inner coils	x
4	neck humbucker, split, neck side coil	
5	neck humbucker	x

terminal wires

- 1 output (to volume pot) or connect to 8
- 2 ground
- 3 free
- 4 bridge humbucker serial link
- 5 neck humbucker +pole
- 6 free
- 7 bridge humbucker +pole
- 8 output (to volume pot)
- 9 free
- 10 ground
- 11 output (to volume pot) or connect to 8 or 1
- 12 neck humbucker serial link

permanent connections:

all -poles and shielding wires to ground