



Eyb Megaswitch® 3.0 Type E

2 humbuckers # 1

position	sound	hum cancelling
1	bridge humbucker	x
2	bridge humbucker split, bridge side coil	
3	bridge humbucker + neck humbucker, both split, outside coils	x
4	neck humbucker, split, neck side coil	
5	neck humbucker	x

terminal	wires
1	ground
2	connect with 1 by soldering bridge
3	free
4	bridge humbucker serial link
5	neck humbucker +pole
6	free
7	bridge humbucker +pole
8	output (to volume pot)
9	free
10	ground
11	connect with 10 by soldering bridge
12	neck humbucker serial link

permanent connections:

all -poles and shielding wires to grund