



Eyb Megaswitch® 3.0 Type E

2 humbuckers + 1 single coil # 1

position	sound	hum cancelling
1	bridge humbucker	x
2	bridge humbucker, split (bridge side coil) and middle pickup	x
3	bridge and neck humbucker	x
4	neck humbucker, split (neck side coil)	x
5	neck humbucker	x

terminal	wires
1	free
2	ground
3	free
4	bridge humbucker serial link
5	neck pickup +pole
6	middle pickup +pole
7	bridge humbucker +pole
8	output (to volume pot)
9	free
10	ground
11	free
12	neck humbucker serial link

permanent connections:

all -poles and shielding wires to ground