



Eyb Megaswitch® 3.0 Type E

**3 single coils # 1
(hum cancelling only when middle pickup is rwrp)**

position	sound	hum cancelling
1	bridge pickup	
2	bridge- and middle pickup	x
3	bridge- and neck pickup	
4	middle- and neck pickup	x
5	neck pickup	

terminal	wires
1	free
2	free
3	free
4	free
5	neck pickup +pole + tone control for neck pickup
6	middle pickup +pole
7	bridge pickup +pole + tone control for bridge pickup
8	output (to volume pot)
9	free
10	free
11	free
12	free

both tone controls have to be equipped with separate capacitors. This way tone control is available for all 5 positions.

permanent connections:

all -poles to ground