



Eyb Megaswitch® 3.0 Type S

3 single coils # 2 (humfree only if middle pickup rwrp)

position	sound	humfree
1	neck pickup	
2	neck- and middle pickup	x
3	all 3 pickups	
4	middle- and bridge pickup	x
5	bridge pickup	

Terminal	wires
A	free
1	middle pickup +pole
B	free
2	tone control for neck pickup
C	connect with 3
3	bridge pickup +pole
4	output (to volume control) connect with 8
5	tone control for middle pickup
6	neck pickup +pole
D	connect with 6
7	free
8	connect with 4

permanente connections:

alle –poles of pickups to ground