



Eyb Megaswitch® 3.0 Type T

**2 single coils # 1
(hum cancelling only when neck pickup is rwrp)**

position	sound	hum cancelling
1	bridge pickup	
2	bridge- and neck pickup	x
3	neck pickup	

terminal	wires
1	neck pickup +pole
2	connect with 1
A	free
3	bridge pickup +pole
4	output (to volume pot), connect with 8 8
B	free
5	connect with 3
C	free
6	free
D	free
7	free
8	output (to volume pot)

permanent connections:

all -poles to ground

Terminals A – D can be used for alternative tone control- or pickup combinations.